

Dane techniczne nagrzewnice elektryczne HeatBox E

Model 1

## Nagrzewnice elektryczne ON/OFF

	D [mm]	L [mm]	C [mm]	C1 [mm]	H [mm]	W [mm]	Moc [kW]	Prąd [A]	Zasilanie	Ilość elementów grzejnych [kW]	Minimalny przepływ powietrza [m <sup>3</sup> /h]
HeatBox E 160 0.5 on/off	160	350	200	57	225	226	0.5	2.17	230	1x0.5	109
HeatBox E 160 1.1 on/off	160	350	200	57	225	226	1.1	4.78	230	1x1.1	109
HeatBox E 160 1.6 on/off	160	350	200	57	225	226	1.6	6.96	230	1x0.5, 1x1.1	109
HeatBox E 160 2.2 on/off	160	350	200	57	225	226	2.2	9.57	230	2x1.1	109
HeatBox E 200 0.75 on/off	200	410	260	57	265	266	0.75	3.26	230	1x0.75	170
HeatBox E 200 1.25 on/off	200	410	260	57	265	266	1.25	5.43	230	1x1.25	170
HeatBox E 200 1.5 on/off	200	410	260	57	265	266	1.5	6.52	230	2x0.75	170
HeatBox E 200 2.0 on/off	200	410	260	57	265	266	2.0	8.70	230	1x0.75, 1x1.25	170
HeatBox E 200 2.5 on/off	200	410	260	57	265	266	2.5	10.87	230	2x1.25	170
HeatBox E 200 2.75 on/off	200	410	260	57	265	266	2.75	11.96	230	2x0.75, 1x1.25	170
HeatBox E 200 3.25 on/off	200	410	260	57	265	266	3.25	14.13	230	1x0.75, 2x1.25	170
HeatBox E 250 1.3 on/off	250	410	260	57	335	336	1.3	5.65	230	1x1.3	265
HeatBox E 250 2.5 on/off	250	410	260	57	335	336	2.5	10.87	230	1x2.5	265
HeatBox E 250 3.9 on/off	250	410	260	57	335	336	3.9	5.65	400	3x1.3	265
HeatBox E 250 5.0 on/off	250	410	260	57	335	336	5.0	7.25	400	2x2.5	265
HeatBox E 250 6.3 on/off	250	410	260	57	335	336	6.3	9.13	400	1x1.3, 2x2.5	265

## Nagrzewnice elektryczne ON/OFF GT

	D [mm]	L [mm]	C [mm]	C1 [mm]	H [mm]	W [mm]	Moc [kW]	Prąd [A]	Zasilanie	Ilość elementów grzejnych [kW]	Minimalny przepływ powietrza [m <sup>3</sup> /h]
HeatBox E 160 0.5 on/off GT	160	350	200	57	225	226	0.5	2.17	230	1x0.5	109
HeatBox E 160 1.1 on/off GT	160	350	200	57	225	226	1.1	4.78	230	1x1.1	109
HeatBox E 160 1.6 on/off GT	160	350	200	57	225	226	1.6	6.96	230	1x0.5, 1x1.1	109
HeatBox E 160 2.2 on/off GT	160	350	200	57	225	226	2.2	9.57	230	2x1.1	109
HeatBox E 200 0.75 on/off GT	200	410	260	57	265	266	0.75	3.26	230	1x0.75	170
HeatBox E 200 1.25 on/off GT	200	410	260	57	265	266	1.25	5.43	230	1x1.25	170
HeatBox E 200 1.5 on/off GT	200	410	260	57	265	266	1.5	6.52	230	2x0.75	170
HeatBox E 200 2.0 on/off GT	200	410	260	57	265	266	2.0	8.70	230	1x0.75, 1x1.25	170
HeatBox E 200 2.5 on/off GT	200	410	260	57	265	266	2.5	10.87	230	2x1.25	170
HeatBox E 200 2.75 on/off GT	200	410	260	57	265	266	2.75	11.96	230	2x0.75, 1x1.25	170
HeatBox E 200 3.25 on/off GT	200	410	260	57	265	266	3.25	14.13	230	1x0.75, 2x1.25	170
HeatBox E 250 1.3 on/off GT	250	410	260	57	335	336	1.3	5.65	230	1x1.3	265
HeatBox E 250 2.5 on/off GT	250	410	260	57	335	336	2.5	10.87	230	1x2.5	265
HeatBox E 250 3.9 on/off GT	250	410	260	57	335	336	3.9	5.65	400	3x1.3	265
HeatBox E 250 5.0 on/off GT	250	410	260	57	335	336	5.0	7.25	400	2x2.5	265
HeatBox E 250 6.3 on/off GT	250	410	260	57	335	336	6.3	9.13	400	1x1.3, 2x2.5	265

## Nagrzewnice elektryczne 0-10V

	D [mm]	L [mm]	C [mm]	C1 [mm]	H [mm]	W [mm]	Moc [kW]	Prąd [A]	Zasilanie	Ilość elementów grzejnych [kW]	Minimalny przepływ powietrza [m <sup>3</sup> /h]
HeatBox E 160 0.5 0-10V	160	350	200	57	225	226	0.5	2.17	230	1x0.5	109
HeatBox E 160 1.1 0-10V	160	350	200	57	225	226	1.1	4.78	230	1x1.1	109
HeatBox E 160 1.6 0-10V	160	350	200	57	225	226	1.6	6.96	230	1x0.5, 1x1.1	109
HeatBox E 160 2.2 0-10V	160	350	200	57	225	226	2.2	9.57	230	2x1.1	109
HeatBox E 200 0.75 0-10V	200	410	260	57	265	266	0.75	3.26	230	1x0.75	170
HeatBox E 200 1.25 0-10V	200	410	260	57	265	266	1.25	5.43	230	1x1.25	170
HeatBox E 200 1.5 0-10V	200	410	260	57	265	266	1.5	6.52	230	2x0.75	170
HeatBox E 200 2.0 0-10V	200	410	260	57	265	266	2.0	8.70	230	1x0.75, 1x1.25	170
HeatBox E 200 2.5 0-10V	200	410	260	57	265	266	2.5	10.87	230	2x1.25	170
HeatBox E 200 2.75 0-10V	200	410	260	57	265	266	2.75	11.96	230	2x0.75, 1x1.25	170
HeatBox E 200 3.25 0-10V	200	410	260	57	265	266	3.25	14.13	230	1x0.75, 2x1.25	170
HeatBox E 250 1.3 0-10V	250	410	260	57	335	336	1.3	5.65	230	1x1.3	265
HeatBox E 250 2.5 0-10V	250	410	260	57	335	336	2.5	10.87	230	1x2.5	265

Model 2

## Nagrzewnice elektryczne ON/OFF GT

	D [mm]	L [mm]	C1 [mm]	H [mm]	Moc [kW]	Prąd [A]	Zasilanie	Ilość elementów grzejnych [kW]	Minimalny przepływ powietrza [m <sup>3</sup> /h]
HeatBox E 400 6.0 on/off GT	400	400	60	500	6.0	8.7	400	6x1	680
HeatBox E 400 9.0 on/off GT	400	500	60	500	9.0	13	400	6x1.5	680

## Nagrzewnice elektryczne 0-10V

	D [mm]	L [mm]	C1 [mm]	H [mm]	Moc [kW]	Prąd [A]	Zasilanie	Ilość elementów grzejnych [kW]	Minimalny przepływ powietrza [m <sup>3</sup> /h]
HeatBox E 250 4.5 0-10V	250	400	40	350	4.5	6.5	400	3x1.5	265
HeatBox E 250 6.0 0-10V	250	400	40	350	6.0	15	400	6x1	265
HeatBox E 400 6.0 0-10V	400	400	60	500	6.0	15	400	4x1.5	680
HeatBox E 400 9.0 0-10V	400	400	60	500	9.0	22.5	400	6x1.5	680